



Then all reset, power on while pushing 'Fast' key and 'Lock' key at the same time.

TECHNICAL LIBRARY

MODEL :FT DX 9000 series

File No.	TL_FTDX9000.doc	Serial Number range	ALL
Date of issue :	06/01/26	Page	2

Type	Frequency Band											Jumper		
	1.8MHz	3.5MHz	5MHz	7MHz	10MHz	14MHz	18MHz	21MHz	24MHz	28MHz	50MHz	JP5001	JP5003	JP5005
EU/ FRG	1.815000 - 1.889999	3.500000 - 3.799999	/	7.000000 - 7.099999	10.100000 - 10.149999	14.000000 - 14.349999	18.068000 - 18.167999	21.000000 - 21.449999	24.890000 - 24.989999	28.000000 - 29.699999	50.080000 - 50.399999		○	○
FRA	1.810000 - 1.849999	↑	/	↑	↑	↑	↑	↑	↑	↑	50.200000 - 51.199999	○		
UK	1.810000 - 1.999999	↑	5.260000, 5.280000, 5.290000, 5.400000, 5.405000	7.000000 - 7.199999	↑	↑	↑	↑	↑	↑	50.000000 - 51.999999		○	
EXP/ AUS	1.800000 - 1.999999	3.500000 - 3.999999	/	7.000000 - 7.299999	↑	↑	↑	↑	↑	↑	50.000000 - 53.999999	○	○	
USA	↑	↑	5.167500, 5.332000, 5.348000, 5.368000, 5.373000, 5.405000	↑	↑	↑	↑	↑	↑	↑	↑			
JPN	1.810000 - 1.824999, 1.907500 - 1.912499	3.500000 - 3.574999, 3.747000 - 3.753999, 3.791000 - 3.804999	4.630000	7.000000 - 7.099999	↑	↑	↑	↑	↑	↑	↑			○